



**General
Mills**

**Making Food
People Love**

850 Purchase Order

X12/V5010/850 : 850 Purchase Order

Company:

General Mills

Modified:

1/11/2018

Notes:

Table of Contents

850 Purchase Order	1
ISA Interchange Control Header	3
GS Functional Group Header	5
ST Transaction Set Header	7
BEG Beginning Segment for Purchase Order	8
REF Reference Information	9
FOB F.O.B. Related Instructions	10
SAC Loop Service, Promotion, Allowance, or Charge Information	11
SAC Service, Promotion, Allowance, or Charge Information	12
ITD Terms of Sale/Deferred Terms of Sale	14
DTM Date/Time Reference	15
TD5 Carrier Details (Routing Sequence/Transit Time)	16
N9 Loop Extended Reference Information	17
N9 Extended Reference Information	18
MTX Text	19
N1 Loop Party Identification	20
N1 Party Identification	21
N3 Party Location	22
N4 Geographic Location	23
PO1 Loop Baseline Item Data	24
PO1 Baseline Item Data	25
PID Loop Product/Item Description	27
PID Product/Item Description	28
PO4 Item Physical Details	29
SAC Loop Service, Promotion, Allowance, or Charge Information	30
SAC Service, Promotion, Allowance, or Charge Information	31
CTT Loop Transaction Totals	33
CTT Transaction Totals	34
AMT Monetary Amount Information	35
SE Transaction Set Trailer	36
GE Functional Group Trailer	37
IEA Interchange Control Trailer	38

850 Purchase Order

Functional Group=**PO**

Purpose: This X12 Transaction Set contains the format and establishes the data contents of the Purchase Order Transaction Set (850) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to the placement of purchase orders for goods and services. This transaction set should not be used to convey purchase order changes or purchase order acknowledgment information.

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	ISA	Interchange Control Header	M	1			Must use
	GS	Functional Group Header	M	1			Must use

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0100	ST	Transaction Set Header	M	1			Must use
0200	BEG	Beginning Segment for Purchase Order	M	1			Must use
0500	REF	Reference Information	O	>1			Used
0800	FOB	F.O.B. Related Instructions	O	>1			Used

LOOP ID - SAC 25

1200	SAC	Service, Promotion, Allowance, or Charge Information	O	1			Used
1300	ITD	Terms of Sale/Deferred Terms of Sale	O	>1			Used
1500	DTM	Date/Time Reference	O	10			Must use
2400	TD5	Carrier Details (Routing Sequence/Transit Time)	O	>1			Used

LOOP ID - N9 1000

2950	N9	Extended Reference Information	O	1			Used
3000	MTX	Text	O	>1			Used

LOOP ID - N1 200

3100	N1	Party Identification	O	1			Must use
3300	N3	Party Location	O	2			Used
3400	N4	Geographic Location	O	>1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
------------	-----------	---------------------	------------	----------------	---------------	--------------	--------------

LOOP ID - PO1 100000 N2/0100L

0100	PO1	Baseline Item Data	M	1		N2/0100	Must use
------	-----	--------------------	---	---	--	---------	----------

LOOP ID - PID 1000

0500	PID	Product/Item Description	O	1			Used
0900	PO4	Item Physical Details	O	>1			Used

LOOP ID - SAC 25

1300	SAC	Service, Promotion, Allowance, or Charge Information	O	1			Used
------	-----	--	---	---	--	--	------

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
------------	-----------	---------------------	------------	----------------	---------------	--------------	--------------

LOOP ID - CTT 1 N3/0100L

0100	CTT	Transaction Totals	O	1		N3/0100	Must use
------	-----	--------------------	---	---	--	---------	----------

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
0200	AMT	Monetary Amount Information	O	1		N3/0200	Used
0300	SE	Transaction Set Trailer	M	1			Must use

Not Defined:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
	GE	Functional Group Trailer	M	1			Must use
	IEA	Interchange Control Trailer	M	1			Must use

Notes:

2/0100L PO102 is required.

2/0100 PO102 is required.

3/0100L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0100 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

3/0200 If AMT is used in the summary area, then AMT01 will = TT and AMT02 will indicate total transaction amount as calculated by the sender.

ISA Interchange Control Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 16

User Option (Usage): Must use

Purpose: To start and identify an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA01	I01	Authorization Information Qualifier	M	ID	2/2	Must use
Description: Code identifying the type of information in the Authorization Information All valid standard codes are used. (Total Codes: 7)						
ISA02	I02	Authorization Information	M	AN	10/10	Must use
Description: Information used for additional identification or authorization of the interchange sender or the data in the interchange; the type of information is set by the Authorization Information Qualifier (I01)						
ISA03	I03	Security Information Qualifier	M	ID	2/2	Must use
Description: Code identifying the type of information in the Security Information All valid standard codes are used. (Total Codes: 2)						
ISA04	I04	Security Information	M	AN	10/10	Must use
Description: This is used for identifying the security information about the interchange sender or the data in the interchange; the type of information is set by the Security Information Qualifier (I03)						
ISA05	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified All valid standard codes are used. (Total Codes: 41)						
ISA06	I06	Interchange Sender ID	M	AN	15/15	Must use
Description: Identification code published by the sender for other parties to use as the receiver ID to route data to them; the sender always codes this value in the sender ID element						
ISA07	I05	Interchange ID Qualifier	M	ID	2/2	Must use
Description: Code indicating the system/method of code structure used to designate the sender or receiver ID element being qualified All valid standard codes are used. (Total Codes: 41)						
ISA08	I07	Interchange Receiver ID	M	AN	15/15	Must use
Description: Identification code published by the receiver of the data; When sending, it is used by the sender as their sending ID, thus other parties sending to them will use this as a receiving ID to route data to them						
ISA09	I08	Interchange Date	M	DT	6/6	Must use
Description: Date of the interchange						
ISA10	I09	Interchange Time	M	TM	4/4	Must use
Description: Time of the interchange						
ISA11	I65	Repetition Separator	M		1/1	Must use
Description: Type is not applicable; the repetition separator is a delimiter and not a data element; this field provides the delimiter used to separate repeated occurrences of a simple data element or a composite data structure; this value must be different than the data element separator, component element separator, and the segment terminator						

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ISA12	I11	Interchange Control Version Number	M	ID	5/5	Must use

Description: Code specifying the version number of the interchange control segments

CodeList Summary (Total Codes: 20, Included: 1)

Code Name

00501 Standards Approved for Publication by ASC X12 Procedures Review Board through October 2003

ISA13	I12	Interchange Control Number	M	N0	9/9	Must use
-------	-----	-----------------------------------	---	----	-----	----------

Description: A control number assigned by the interchange sender

ISA14	I13	Acknowledgment Requested	M	ID	1/1	Must use
-------	-----	---------------------------------	---	----	-----	----------

Description: Code indicating sender's request for an interchange acknowledgment

All valid standard codes are used. (Total Codes: 2)

ISA15	I14	Interchange Usage Indicator	M	ID	1/1	Must use
-------	-----	------------------------------------	---	----	-----	----------

Description: Code indicating whether data enclosed by this interchange envelope is test, production or information

CodeList Summary (Total Codes: 3, Included: 1)

Code Name

P Production Data

ISA16	I15	Component Element Separator	M		1/1	Must use
-------	-----	------------------------------------	---	--	-----	----------

Description: Type is not applicable; the component element separator is a delimiter and not a data element; this field provides the delimiter used to separate component data elements within a composite data structure; this value must be different than the data element separator and the segment terminator

GS Functional Group Header

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 8

User Option (Usage): Must use

Purpose: To indicate the beginning of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GS01	479	Functional Identifier Code	M	ID	2/2	Must use
Description: Code identifying a group of application related transaction sets						
CodeList Summary (Total Codes: 260, Included: 1)						
<u>Code</u> <u>Name</u>						
PO Purchase Order (850)						
GS02	142	Application Sender's Code	M	AN	2/15	Must use
Description: Code identifying party sending transmission; codes agreed to by trading partners						
GS03	124	Application Receiver's Code	M	AN	2/15	Must use
Description: Code identifying party receiving transmission; codes agreed to by trading partners						
GS04	373	Date	M	DT	8/8	Must use
Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year						
GS05	337	Time	M	TM	4/8	Must use
Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)						
GS06	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						
GS07	455	Responsible Agency Code	M	ID	1/2	Must use
Description: Code identifying the issuer of the standard; this code is used in conjunction with Data Element 480						
CodeList Summary (Total Codes: 2, Included: 1)						
<u>Code</u> <u>Name</u>						
X Accredited Standards Committee X12						
GS08	480	Version / Release / Industry Identifier Code	M	AN	1/12	Must use
Description: Code indicating the version, release, subrelease, and industry identifier of the EDI standard being used, including the GS and GE segments; if code in DE455 in GS segment is X, then in DE 480 positions 1-3 are the version number; positions 4-6 are the release and subrelease, level of the version; and positions 7-12 are the industry or trade association identifiers (optionally assigned by user); if code in DE455 in GS segment is T, then other formats are allowed						
CodeList Summary (Total Codes: 54, Included: 1)						
<u>Code</u> <u>Name</u>						
005010 Standards Approved for Publication by ASC X12 Procedures Review Board through October 2003						

Semantics:

1. GS04 is the group date.

2. GS05 is the group time.
3. The data interchange control number GS06 in this header must be identical to the same data element in the associated functional group trailer, GE02.

Comments:

1. A functional group of related transaction sets, within the scope of X12 standards, consists of a collection of similar transaction sets enclosed by a functional group header and a functional group trailer.

ST Transaction Set Header

Pos: 0100	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use

Description: Code uniquely identifying a Transaction Set

CodeList Summary (Total Codes: 318, Included: 1)

<u>Code</u>	<u>Name</u>
-------------	-------------

850	Purchase Order
-----	----------------

ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
------	-----	--------------------------------	---	----	-----	----------

Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set

Semantics:

1. The transaction set identifier (ST01) is used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).
2. The implementation convention reference (ST03) is used by the translation routines of the interchange partners to select the appropriate implementation convention to match the transaction set definition. When used, this implementation convention reference takes precedence over the implementation reference specified in the GS08.

BEG Beginning Segment for Purchase Order

Pos: 0200	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 4

User Option (Usage): Must use

Purpose: To indicate the beginning of the Purchase Order Transaction Set and transmit identifying numbers and dates

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
BEG01	353	Transaction Set Purpose Code	M	ID	2/2	Must use

Description: Code identifying purpose of transaction set

CodeList Summary (Total Codes: 66, Included: 1)

Code Name

00 Original

BEG02	92	Purchase Order Type Code	M	ID	2/2	Must use
-------	----	--------------------------	---	----	-----	----------

Description: Code specifying the type of Purchase Order

CodeList Summary (Total Codes: 76, Included: 2)

Code Name

NE New Order

SA Stand-alone Order

BEG03	324	Purchase Order Number	M	AN	1/22	Must use
-------	-----	-----------------------	---	----	------	----------

Description: Identifying number for Purchase Order assigned by the orderer/purchaser

BEG05	373	Date	M	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

Semantics:

1. BEG05 is the date assigned by the purchaser to purchase order.

REF Reference Information

Pos: 0500	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify identifying information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
REF01	128	Reference Identification Qualifier	M	ID	2/3	Must use

Description: Code qualifying the Reference Identification

General Mills Note: All standard codes will be processed and stored on the order. Common values are highlighted below.

CodeList Summary (Total Codes: 1731, Included: 4)

Code Name

AN Associated Purchase Orders
DP Department Number
IA Internal Vendor Number
MR Merchandise Type Code

REF02	127	Reference Identification	X	AN	1/50	Must use
-------	-----	--------------------------	---	----	------	----------

Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier

Syntax Rules:

1. R0203 - At least one of REF02 or REF03 is required.

Semantics:

1. REF04 contains data relating to the value cited in REF02.

FOB F.O.B. Related Instructions

Pos: 0800	Max: >1
Heading - Optional	
Loop: N/A	Elements: 2

User Option (Usage): Used

Purpose: To specify transportation instructions relating to shipment

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
FOB01	146	Shipment Method of Payment	M	ID	2/2	Must use

Description: Code identifying payment terms for transportation charges

CodeList Summary (Total Codes: 31, Included: 2)

Code Name

CC Collect

PP Prepaid (by Seller)

FOB02	309	Location Qualifier	X	ID	1/2	Used
-------	-----	--------------------	---	----	-----	------

Description: Code identifying type of location

CodeList Summary (Total Codes: 184, Included: 1)

Code Name

OR Origin (Shipping Point)

Syntax Rules:

1. C0302 - If FOB03 is present, then FOB02 is required.
2. C0405 - If FOB04 is present, then FOB05 is required.
3. C0706 - If FOB07 is present, then FOB06 is required.
4. C0809 - If FOB08 is present, then FOB09 is required.

Semantics:

1. FOB01 indicates which party will pay the carrier.
2. FOB02 is the code specifying transportation responsibility location.
3. FOB06 is the code specifying the title passage location.
4. FOB08 is the code specifying the point at which the risk of loss transfers. This may be different than the location specified in FOB02/FOB03 and FOB06/FOB07.

Loop Service, Promotion, Allowance, or Charge Information

Pos: 1200	Repeat: 25
Optional	
Loop: SAC	Elements: N/A

User Option (Usage): Used

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Loop Summary:

Pos	Id	Segment Name	Req	Max Use	Repeat	Usage
1200	SAC	Service, Promotion, Allowance, or Charge Information	O	1		Used

SAC Service, Promotion, Allowance, or Charge Information

Pos: 1200	Max: 1
Heading - Optional	
Loop: SAC	Elements: 4

User Option (Usage): Used

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC01	248	Allowance or Charge Indicator	M	ID	1/1	Must use

Description: Code which indicates an allowance or charge for the service specified

CodeList Summary (Total Codes: 7, Included: 2)

Code Name

A	Allowance
C	Charge

SAC02	1300	Service, Promotion, Allowance, or Charge Code	X	ID	4/4	Used
-------	------	---	---	----	-----	------

Description: Code identifying the service, promotion, allowance, or charge

General Mills Note: All Standard code values will be processed.

SAC05	610	Amount	O	N2	1/15	Used
-------	-----	--------	---	----	------	------

Description: Monetary amount

SAC07	332	Percent, Decimal Format	X	R	1/6	Used
-------	-----	-------------------------	---	---	-----	------

Description: Percent given in decimal format (e.g., 0.0 through 100.0 represents 0% through 100%)

Syntax Rules:

1. R0203 - At least one of SAC02 or SAC03 is required.
2. P0304 - If either SAC03 or SAC04 is present, then the other is required.
3. P0607 - If either SAC06 or SAC07 is present, then the other is required.
4. P0910 - If either SAC09 or SAC10 is present, then the other is required.
5. C1110 - If SAC11 is present, then SAC10 is required.
6. C1413 - If SAC14 is present, then SAC13 is required.
7. C1615 - If SAC16 is present, then SAC15 is required.

Semantics:

1. If SAC01 is "A" or "C", then at least one of SAC05, SAC07, or SAC08 is required.
2. SAC05 is the total amount for the service, promotion, allowance, or charge.
3. If SAC05 is present with SAC07 or SAC08, then SAC05 takes precedence.
4. SAC08 is the allowance or charge rate per unit.
5. SAC10 and SAC11 is the quantity basis when the allowance or charge quantity is different from the purchase order or invoice quantity.
6. SAC10 and SAC11 used together indicate a quantity range, which could be a dollar amount, that is applicable to service, promotion, allowance, or charge.
7. SAC13 is used in conjunction with SAC02 or SAC04 to provide a specific reference number as identified by the code used.
8. SAC14 is used in conjunction with SAC13 to identify an option when there is more than one option of the promotion.
9. SAC16 is used to identify the language being used in SAC15.

Comments:

1. SAC04 may be used to uniquely identify the service, promotion, allowance, or charge. In addition, it may be used in conjunction with SAC03 to further define SAC02.

2. In some business applications, it is necessary to advise the trading partner of the actual dollar amount that a particular allowance, charge, or promotion was based on to reduce ambiguity. This amount is commonly referred to as "Dollar Basis Amount". It is represented in the SAC segment in SAC10 using the qualifier "DO" - Dollars in SAC09.

ITD Terms of Sale/Deferred Terms of Sale

Pos: 1300	Max: >1
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Used

Purpose: To specify terms of sale

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ITD03	338	Terms Discount Percent	O	R	1/6	Used
Description: Terms discount percentage, expressed as a percent, available to the purchaser if an invoice is paid on or before the Terms Discount Due Date						
ITD05	351	Terms Discount Days Due	X	N0	1/3	Used
Description: Number of days in the terms discount period by which payment is due if terms discount is earned						
ITD07	386	Terms Net Days	O	N0	1/3	Used
Description: Number of days until total invoice amount is due (discount not applicable)						

Syntax Rules:

1. L03040513 - If ITD03 is present, then at least one of ITD04, ITD05 or ITD13 is required.
2. L08040513 - If ITD08 is present, then at least one of ITD04, ITD05 or ITD13 is required.
3. L091011 - If ITD09 is present, then at least one of ITD10 or ITD11 is required.

Semantics:

1. ITD15 is the percentage applied to a base amount used to determine a late payment charge.

Comments:

1. If the code in ITD01 is "04", then ITD07 or ITD09 is required and either ITD10 or ITD11 is required; if the code in ITD01 is "05", then ITD06 or ITD07 is required.

DTM Date/Time Reference

Pos: 1500	Max: 10
Heading - Optional	
Loop: N/A	Elements: 3

User Option (Usage): Must use

Purpose: To specify pertinent dates and times

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
DTM01	374	Date/Time Qualifier	M	ID	3/3	Must use

Description: Code specifying type of date or time, or both date and time

CodeList Summary (Total Codes: 1280, Included: 2)

Code Name

002 Delivery Requested

010 Requested Ship

DTM02	373	Date	X	DT	8/8	Must use
-------	-----	------	---	----	-----	----------

Description: Date expressed as CCYYMMDD where CC represents the first two digits of the calendar year

DTM03	337	Time	X	TM	4/8	Used
-------	-----	------	---	----	-----	------

Description: Time expressed in 24-hour clock time as follows: HHMM, or HHMMSS, or HHMMSSD, or HHMMSSDD, where H = hours (00-23), M = minutes (00-59), S = integer seconds (00-59) and DD = decimal seconds; decimal seconds are expressed as follows: D = tenths (0-9) and DD = hundredths (00-99)

Syntax Rules:

1. R020305 - At least one of DTM02, DTM03 or DTM05 is required.
2. C0403 - If DTM04 is present, then DTM03 is required.
3. P0506 - If either DTM05 or DTM06 is present, then the other is required.

TD5 Carrier Details (Routing Sequence/Transit Time)

Pos: 2400	Max: >1
Heading - Optional	
Loop: N/A	Elements: 1

User Option (Usage): Used

Purpose: To specify the carrier and sequence of routing and provide transit time information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
TD504	91	Transportation Method/Type Code	X	ID	1/2	Used

Description: Code specifying the method or type of transportation for the shipment

CodeList Summary (Total Codes: 80, Included: 4)

<u>Code</u>	<u>Name</u>
H	Customer Pickup
K	Backhaul
M	Motor (Common Carrier)
CE	Customer Pickup / Customer's Expense

Syntax Rules:

1. R0204050612 - At least one of TD502, TD504, TD505, TD506 or TD512 is required.
2. C0203 - If TD502 is present, then TD503 is required.
3. C0708 - If TD507 is present, then TD508 is required.
4. C1011 - If TD510 is present, then TD511 is required.
5. C1312 - If TD513 is present, then TD512 is required.
6. C1413 - If TD514 is present, then TD513 is required.
7. C1512 - If TD515 is present, then TD512 is required.

Semantics:

1. TD515 is the country where the service is to be performed.

Comments:

1. When specifying a routing sequence to be used for the shipment movement in lieu of specifying each carrier within the movement, use TD502 to identify the party responsible for defining the routing sequence, and use TD503 to identify the actual routing sequence, specified by the party identified in TD502.

Loop Extended Reference Information

Pos: 2950	Repeat: 1000
Optional	
Loop: N9	Elements: N/A

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
2950	N9	Extended Reference Information	O	1		Used
3000	MTX	Text	O	>1		Used

N9 Extended Reference Information

Pos: 2950	Max: 1
Heading - Optional	
Loop: N9	Elements: 2

User Option (Usage): Used

Purpose: To transmit identifying information as specified by the Reference Identification Qualifier

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N901	128	Reference Identification Qualifier	M	ID	2/3	Must use
Description: Code qualifying the Reference Identification						
General Mills Note: All standard values will processed on the order, and sent back on the EDI invoice.						
N902	127	Reference Identification	X	AN	1/50	Must use
Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier						
General Mills Note: Both N901 & N902 values will be processed on the order and sent back on the EDI invoice.						

Syntax Rules:

1. R0203 - At least one of N902 or N903 is required.
2. C0605 - If N906 is present, then N905 is required.

Semantics:

1. N906 reflects the time zone which the time reflects.
2. N907 contains data relating to the value cited in N902.

MTX Text

Pos: 3000	Max: >1
Heading - Optional	
Loop: N9	Elements: 1

User Option (Usage): Used
Purpose: To specify textual data

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
MTX02	1551	Textual Data	X	AN	1/4096	Must use
Description: To transmit large volumes of message text						
General Mills Note: This text information will be processed on the order.						

Syntax Rules:

- 1. C0102 - If MTX01 is present, then MTX02 is required.
- 2. C0302 - If MTX03 is present, then MTX02 is required.
- 3. C0504 - If MTX05 is present, then MTX04 is required.

Semantics:

- 1. MTX05 is the number of lines to advance before printing.

Comments:

- 1. If MTX04 is "AA - Advance the specific number of lines before print", then MTX05 is required.

Loop Party Identification

Pos: 3100	Repeat: 200
Optional	
Loop: N1	Elements: N/A

User Option (Usage): Must use
Purpose: To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
3100	N1	Party Identification	O	1		Must use
3300	N3	Party Location	O	2		Used
3400	N4	Geographic Location	O	>1		Used

N1 Party Identification

Pos: 3100	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Must use

Purpose: To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use

Description: Code identifying an organizational entity, a physical location, property or an individual

CodeList Summary (Total Codes: 1500, Included: 6)

Code Name

BT	Bill-to-Party
BY	Buying Party (Purchaser)
CN	Consignee
ST	Ship To
SU	Supplier/Manufacturer
VN	Vendor

N102	93	Name	X	AN	1/60	Used
------	----	------	---	----	------	------

Description: Free-form name

N103	66	Identification Code Qualifier	X	ID	1/2	Used
------	----	-------------------------------	---	----	-----	------

Description: Code designating the system/method of code structure used for Identification Code (67)

CodeList Summary (Total Codes: 241, Included: 3)

Code Name

9	D-U-N-S+4, D-U-N-S Number with Four Character Suffix
92	Assigned by Buyer or Buyer's Agent
UL	Global Location Number (GLN)

Description: A globally unique 13 digit code for the identification of a legal, functional or physical location within the Uniform Code Council (UCC) and International Article Number Association (EAN) numbering system

N104	67	Identification Code	X	AN	2/80	Used
------	----	---------------------	---	----	------	------

Description: Code identifying a party or other code

General Mills Note: The N104 value is used to determine the shipping address for the order.

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N3 Party Location

Pos: 3300	Max: 2
Heading - Optional	
Loop: N1	Elements: 2

User Option (Usage): Used
Purpose: To specify the location of the named party

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				
N302	166	Address Information	O	AN	1/55	Used
		Description: Address information				

N4 Geographic Location

Pos: 3400	Max: >1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

Purpose: To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
Description: Free-form text for city name						
N402	156	State or Province Code	X	ID	2/2	Must use
Description: Code (Standard State/Province) as defined by appropriate government agency						
N403	116	Postal Code	O	ID	3/15	Used
Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)						

Syntax Rules:

1. E0207 - Only one of N402 or N407 may be present.
2. C0605 - If N406 is present, then N405 is required.
3. C0704 - If N407 is present, then N404 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop Baseline Item Data

Pos: 0100	Repeat: 100000
Mandatory	
Loop: PO1	Elements: N/A

User Option (Usage): Must use
Purpose: To specify basic and most frequently used line item data

Loop Summary:

Pos	Id	Segment Name	Req	Max Use	Repeat	Usage
0100	PO1	Baseline Item Data	M	1		Must use
0500		Loop PID	O		1000	Used
0900	PO4	Item Physical Details	O	>1		Used
1300		Loop SAC	O		25	Used

PO1 Baseline Item Data

Pos: 0100	Max: 1
Detail - Mandatory	
Loop: PO1	Elements: 8

User Option (Usage): Must use

Purpose: To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	380	Quantity	X	R	1/15	Must use
		Description: Numeric value of quantity				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Must use
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		CodeList Summary (Total Codes: 844, Included: 3)				
		<u>Code</u>	<u>Name</u>			
		CA	Case			
		EA	Each			
		PL	Pallet/Unit Load			
PO104	212	Unit Price	X	R	1/17	Must use
		Description: Price per unit of product, service, commodity, etc.				
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		General Mills Note: <i>The correct materials are determined by first looking at the UK (Case GTIN) or the UA (UPC Case) Codes.</i>				
		CodeList Summary (Total Codes: 520, Included: 2)				
		<u>Code</u>	<u>Name</u>			
		CA	Case			
		UK	GTIN 14-digit Data Structure			
			Description: <i>Data structure for the 14 digit EAN.UCC (EAN International.Uniform Code Council) Global Trade Item Number (GTIN)</i>			
PO107	234	Product/Service ID	X	AN	1/48	Must use
		Description: Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		General Mills Note: <i>The customer material number can be sent, but is used for informational purposes only. The UPC Package code 'UP' is the last check to find a material number for the order.</i>				
		CodeList Summary (Total Codes: 519, Included: 4)				
		<u>Code</u>	<u>Name</u>			
		CB	Buyer's Catalog Number			
		IN	Buyer's Item Number			
		UP	UCC - 12			
			Description: <i>Data structure for the 12 digit EAN.UCC (EAN International.Uniform Code Council) Global Trade Identification Number (GTIN). Also known as the Universal Product Code (U.P.C.)</i>			

Code Name

VN Vendor's (Seller's) Item Number

PO109	234	Product/Service ID	X	AN	1/48	Used
-------	-----	---------------------------	---	----	------	------

Description: Identifying number for a product or service**Syntax Rules:**

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Semantics:

1. PO102 is quantity ordered.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop Product/Item Description

Pos: 0500	Repeat: 1000
Optional	
Loop: PID	Elements: N/A

User Option (Usage): Used
Purpose: To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0500	PID	Product/Item Description	O	1		Used

PID Product/Item Description

Pos: 0500	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

Purpose: To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>				
PID01	349	Item Description Type	M	ID	1/1	Must use				
Description: Code indicating the format of a description										
CodeList Summary (Total Codes: 3, Included: 1)										
<table><tr><th><u>Code</u></th><th><u>Name</u></th></tr><tr><td>F</td><td>Free-form</td></tr></table>							<u>Code</u>	<u>Name</u>	F	Free-form
<u>Code</u>	<u>Name</u>									
F	Free-form									
PID05	352	Description	X	AN	1/80	Must use				
Description: A free-form description to clarify the related data elements and their content										

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

PO4 Item Physical Details

Pos: 0900	Max: >1
Detail - Optional	
Loop: PO1	Elements: 3

User Option (Usage): Used

Purpose: To specify the physical qualities, packaging, weights, and dimensions relating to the item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO401	356	Pack	O	N0	1/6	Used
		Description: The number of inner containers, or number of eaches if there are no inner containers, per outer container				
PO402	357	Size	X	R	1/8	Used
		Description: Size of supplier units in pack				
PO403	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				

Syntax Rules:

1. P0203 - If either PO402 or PO403 is present, then the other is required.
2. C0506 - If PO405 is present, then PO406 is required.
3. P0607 - If either PO406 or PO407 is present, then the other is required.
4. P0809 - If either PO408 or PO409 is present, then the other is required.
5. C1013 - If PO410 is present, then PO413 is required.
6. C1113 - If PO411 is present, then PO413 is required.
7. C1213 - If PO412 is present, then PO413 is required.
8. L13101112 - If PO413 is present, then at least one of PO410, PO411 or PO412 is required.
9. C1716 - If PO417 is present, then PO416 is required.
10. C1804 - If PO418 is present, then PO404 is required.

Semantics:

1. PO415 is used to indicate the relative layer of this package or range of packages within the layers of packaging. Relative Position 1 (value R1) is the innermost package.
2. PO416 is the package identifier or the beginning package identifier in a range of identifiers.
3. PO417 is the ending package identifier in a range of identifiers.
4. PO418 is the number of packages in this layer.

Comments:

1. PO403 - The "Unit or Basis for Measure Code" in this segment position is for purposes of defining the unit of measure of the "Size" identified in the PO402. For example: If the carton contains 24 12-Ounce packages, it would be described as follows:
Data element 356 = "24"; Data element 357 = "12"; Data element 355 = "OZ".
2. PO413 defines the unit of measure for PO410, PO411, and PO412.

Loop Service, Promotion, Allowance, or Charge Information

Pos: 1300Repeat: 25
Optional
Loop: SACElements: N/A

User Option (Usage): Used

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Loop Summary:

Pos	Id	Segment Name	Req	Max Use	Repeat	Usage
1300	SAC	Service, Promotion, Allowance, or Charge Information	O	1		Used

SAC Service, Promotion, Allowance, or Charge Information

Pos: 1300	Max: 1
Detail - Optional	
Loop: SAC	Elements: 8

User Option (Usage): Used

Purpose: To request or identify a service, promotion, allowance, or charge; to specify the amount or percentage for the service, promotion, allowance, or charge

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SAC01	248	Allowance or Charge Indicator	M	ID	1/1	Must use

Description: Code which indicates an allowance or charge for the service specified

General Mills Note: This segment is used to provide charges and allowances at the line item level.

CodeList Summary (Total Codes: 7, Included: 2)

Code Name

A Allowance

C Charge

SAC02	1300	Service, Promotion, Allowance, or Charge Code	X	ID	4/4	Must use
-------	------	---	---	----	-----	----------

Description: Code identifying the service, promotion, allowance, or charge

General Mills Note: All Standard values will be processed.

SAC05	610	Amount	O	N2	1/15	Used
-------	-----	--------	---	----	------	------

Description: Monetary amount

SAC07	332	Percent, Decimal Format	X	R	1/6	Used
-------	-----	-------------------------	---	---	-----	------

Description: Percent given in decimal format (e.g., 0.0 through 100.0 represents 0% through 100%)

SAC08	118	Rate	O	R	1/9	Must use
-------	-----	------	---	---	-----	----------

Description: Rate expressed in the standard monetary denomination for the currency specified

SAC09	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
-------	-----	------------------------------------	---	----	-----	------

Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken

General Mills Note: Typically charges and allowances are set up at the case level 'CA'.

CodeList Summary (Total Codes: 844, Included: 1)

Code Name

CA Case

SAC11	380	Quantity	O	R	1/15	Used
-------	-----	----------	---	---	------	------

Description: Numeric value of quantity

SAC12	331	Allowance or Charge Method of Handling Code	O	ID	2/2	Used
-------	-----	---	---	----	-----	------

Description: Code indicating method of handling for an allowance or charge

CodeList Summary (Total Codes: 22, Included: 2)

Code Name

02 Off Invoice

05 Charge to be Paid by Vendor

Syntax Rules:

1. R0203 - At least one of SAC02 or SAC03 is required.
2. P0304 - If either SAC03 or SAC04 is present, then the other is required.
3. P0607 - If either SAC06 or SAC07 is present, then the other is required.
4. P0910 - If either SAC09 or SAC10 is present, then the other is required.
5. C1110 - If SAC11 is present, then SAC10 is required.
6. C1413 - If SAC14 is present, then SAC13 is required.
7. C1615 - If SAC16 is present, then SAC15 is required.

Semantics:

1. If SAC01 is "A" or "C", then at least one of SAC05, SAC07, or SAC08 is required.
2. SAC05 is the total amount for the service, promotion, allowance, or charge.
3. If SAC05 is present with SAC07 or SAC08, then SAC05 takes precedence.
4. SAC08 is the allowance or charge rate per unit.
5. SAC10 and SAC11 is the quantity basis when the allowance or charge quantity is different from the purchase order or invoice quantity.
6. SAC10 and SAC11 used together indicate a quantity range, which could be a dollar amount, that is applicable to service, promotion, allowance, or charge.
7. SAC13 is used in conjunction with SAC02 or SAC04 to provide a specific reference number as identified by the code used.
8. SAC14 is used in conjunction with SAC13 to identify an option when there is more than one option of the promotion.
9. SAC16 is used to identify the language being used in SAC15.

Comments:

1. SAC04 may be used to uniquely identify the service, promotion, allowance, or charge. In addition, it may be used in conjunction with SAC03 to further define SAC02.
2. In some business applications, it is necessary to advise the trading partner of the actual dollar amount that a particular allowance, charge, or promotion was based on to reduce ambiguity. This amount is commonly referred to as "Dollar Basis Amount". It is represented in the SAC segment in SAC10 using the qualifier "DO" - Dollars in SAC09.

Loop Transaction Totals

Pos: 0100	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Must use
Purpose: To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
0100	CTT	Transaction Totals	O	1		Must use
0200	AMT	Monetary Amount Information	O	1		Used

CTT Transaction Totals

Pos: 0100	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Must use

Purpose: To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	N0	1/6	Must use
Description: Total number of line items in the transaction set						
General Mills Note: <i>The number of line items is required to process an order.</i>						
CTT02	347	Hash Total	O	R	1/10	Used
Description: Sum of values of the specified data element. All values in the data element will be summed without regard to decimal points (explicit or implicit) or signs. Truncation will occur on the left most digits if the sum is greater than the maximum size of the hash total of the data element. Example: -.0018 First occurrence of value being hashed. .18 Second occurrence of value being hashed. 1.8 Third occurrence of value being hashed. 18.01 Fourth occurrence of value being hashed. 18E2 Fifth occurrence of value being hashed. ----- 1873 Hash Total						

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

AMT Monetary Amount Information

Pos: 0200	Max: 1
Summary - Optional	
Loop: CTT	Elements: 2

User Option (Usage): Used
Purpose: To indicate the total monetary amount

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage						
AMT01	522	Amount Qualifier Code	M	ID	1/3	Must use						
Description: Code to qualify amount												
General Mills Note: This should be the gross value of the purchase order.												
CodeList Summary (Total Codes: 1765, Included: 2)												
<table><tr><th>Code</th><th>Name</th></tr><tr><td>GV</td><td>Gross Value</td></tr><tr><td>TT</td><td>Total Transaction Amount</td></tr></table>							Code	Name	GV	Gross Value	TT	Total Transaction Amount
Code	Name											
GV	Gross Value											
TT	Total Transaction Amount											
AMT02	782	Monetary Amount	M	R	1/18	Must use						
Description: Monetary amount												

SE Transaction Set Trailer

Pos: 0300	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

Ref	Id	Element Name	Req	Type	Min/Max	Usage
SE01	96	Number of Included Segments	M	N0	1/10	Must use
Description: Total number of segments included in a transaction set including ST and SE segments						
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set						

Comments:

- 1. SE is the last segment of each transaction set.

GE Functional Group Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

Purpose: To indicate the end of a functional group and to provide control information

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
GE01	97	Number of Transaction Sets Included	M	N0	1/6	Must use
Description: Total number of transaction sets included in the functional group or interchange (transmission) group terminated by the trailer containing this data element						
GE02	28	Group Control Number	M	N0	1/9	Must use
Description: Assigned number originated and maintained by the sender						

Semantics:

1. The data interchange control number GE02 in this trailer must be identical to the same data element in the associated functional group header, GS06.

Comments:

1. The use of identical data interchange control numbers in the associated functional group header and trailer is designed to maximize functional group integrity. The control number is the same as that used in the corresponding header.

IEA Interchange Control Trailer

Pos:	Max: 1
Not Defined - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use
Purpose: To define the end of an interchange of zero or more functional groups and interchange-related control segments

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
IEA01	I16	Number of Included Functional Groups	M	N0	1/5	Must use
Description: A count of the number of functional groups included in an interchange						
IEA02	I12	Interchange Control Number	M	N0	9/9	Must use
Description: A control number assigned by the interchange sender						